- 1 Install the driver of your USB to RS232 converter, and check the COM number
- 2 Run T-boot.exe, please turst this softwer or turn off your antivirus programe



3 open firmware 'AP\_CCU\_V3.3.1\_170111.tfu'

T-Boot	0	83		
Help				
Fireware Open Fireware Select	Firmware Serial Pert Sel	eet		
Firmware Update	2	_		
Status		_		
	57			
Ready	V			
●打开				×
TC-106 Firmware_170111 + CCU +	,	• + / 旅家 cci	<i>V</i>	٩
组织 ▼ 新建文件夹			)# • E	
▲ ☆ 枚離夹 ▲ 名称 ▲	修改日期	奥型	大小	
🙀 下號	2017/1/11 14:20	文件夹		
■ 貞面	2017/1/11 14:05	TFU 文件 34 KB		KB
3. 最近访问的位置				
> 🗃 税類				
> 🔛 图片				
> 🖸 文档				
▷ 👌 當乐				
* (學 计算机				
文件名(N):		• (*.tfu)		
		打开(0)		*

4 select before COM Port to connect the CCU

O T-Boot	
Help select COM Port(install driv	er first)
Firmware Firmware Select C:\Users\Jun\Desktop\TC-106 Firmware_170111\CCU\AP_CCU_V3.3.1 Firmware Update	Serial Port Select
Status Firmware: TAPC-100, Version: V3.3.1	
Ready	

- 5 Power on the CCU, and the LED will be always on (means the hardware connected).
- 6 press [Firmware Update] button to update CCU, the LED will be flashing
- 7 Wait when updating, and please restart the CCU after update.